

## CAST ALUMINUM BRACKETS



**WB5**

Contemporary Wall Bracket pre-wired w/20" pigtail for easy installation with 3" Post Mount Fixture  
Max. Fixture Width: 16". I.D. = 3"  
H = 6", W = 4 1/2", E = 12 1/2"  
Powdercoated Finish  
**SPECIFY: (BK) Black (WH) White or (BZ) Bronze**



**PB5**

Post Bracket pre-wired w/20" pigtail for easy installation with 3" Post Mount Fixture.  
Designed to mount to Wave Lighting's 3" Commercial Posts. PB5-CAP Included.  
Max. Fixture Width: 16". I.D. = 3"  
H = 9 1/2", W = 4 1/2", E = 16 1/2"  
Powdercoated Finish  
**SPECIFY: (BK) Black (WH) White or (BZ) Bronze**

SEE PAGE 46



**PB5-2**

Post Bracket pre-wired w/20" pigtail for easy installation with 3" Post Mount Fixtures.  
Designed to mount 2 Fixtures to Wave Lighting's 3" Commercial Posts. PB5-CAP Incl.  
Max. Fixture Width: 16". I.D. = 3"  
H = 9 1/2", W = 4 1/2", E = 29"  
Powdercoated Finish  
**SPECIFY: (BK) Black (WH) White or (BZ) Bronze**



**PB5-3**

Post Bracket pre-wired w/20" pigtail for easy installation with 3" Post Mount Fixtures.  
Designed to mount 3 Fixtures to Wave Lighting's 3" Commercial Posts  
Max. Fixture Width: 14". I.D. = 3"  
H = 9", W = 4 1/2", E = 29"  
Powdercoated Finish  
**SPECIFY: (BK) Black (WH) White or (BZ) Bronze**



**PB5-CAP**

Cap for 3" Post I.D. = 3" Powdercoated Finish  
**SPECIFY: (BK) Black (WH) White or (BZ) Bronze**

See Safety Note on page 55

## CAST ALUMINUM FITTERS



**1784**

Style A Fitter for Globes & Acorns with 8" Neck  
H = 11", W = 10 1/4", I.D. = 3"



**1785**

Style B Fitter for Globes & Acorns with 8" Neck  
H = 10 1/2", W = 10 1/4", I.D. = 3"

4Kv Medium Base Porcelain Socket Standard


**Specify Option: (MG) Mogul Socket**  
Powdercoated Finish **Specify: (BK) Black, (BZ) Bronze or (WH) White**

## GLASS REFRACTORS




**1000135**

for Mogul Base Socket Type V Distribution  
H = 6 5/8", Dia. = 6 1/8"  
Top I.D. = 5 1/4"  
Bottom I.D. = 3 1/4"



**1000137**

for Mogul Base Socket Type III Distribution  
H = 6 5/8", Dia. = 6 1/8"  
Top I.D. = 5 1/4"  
Bottom I.D. = 3 1/4"



**1000138**

for Medium Base Socket Type V Distribution  
H = 4 7/8", Dia. = 4 3/4"  
Top I.D. = 4"  
Bottom I.D. = 3"

## DARK SKY REFLECTORS



**DS120**

Bottom Mount Kit for Mogul Base Sockets

**DS130**

Bottom Mount Kit for Medium Base Sockets



**DS140**

Bottom Mount Kit for 6" Glass Refractors (refractor not included)

## CAST ALUMINUM DECORATIVE BASE COVERS

Decorative Base Covers come as a two piece system, and can be installed over existing Surface Mounted Posts. **3BC9** and **4BC9** are one piece system.

### FOR MOST 3" DIAMETER POSTS



**3BC1**

Dia.: 13 1/8"  
Height: 24 1/8"



**3BC2**

Dia.: 11 1/2"  
Height: 13 5/8"



**3BC3**

Dia.: 11"  
Height: 26 3/8"



**3BC6**

Dia.: 11"  
Height: 9 5/8"



**3BC9**

Dia.: 10"  
Height: 3 1/2"  
Top I.D.: 4 1/8"

### FOR MOST 4" DIAMETER POSTS



**4BC1**

Dia.: 15"  
Height: 27 5/8"



**4BC3**

Dia.: 12 1/8"  
Height: 29"



**4BC6**

Dia.: 12"  
Height: 9 5/8"



**4BC9**

Dia.: 11"  
Height: 3 1/2"  
Top I.D.: 5 3/8"

Powdercoated Finish - **SPECIFY: (BK) Black, (BZ) Bronze or (WH) White**

Posts sold separately.

Specifications subject to change without notice.